Settings of the Bluetooth Printer

1. Open the file—"Printer TEST V3.0C" in the folder named as "Tools" in the optical disk.

Then start Printer software and follow the steps to set the printer. See the picture followed.

😤 Printer TEST V3.0C			×
Port Select	COM 2 OUSB ONET	Printer Type O POS-58 O	POS-76 1
LPT Set	COM Set		
LPT1 ·	COM1 9600	▼ RTS	×
NET Set Local IP:	192 . 168 . 123 . 120	Refresh	
Printer IP:	192 . 168 . 19 . 100	Connect	Ping
New IP:	192 . 168 . 19 . 100	Set New IP	NetMonitor
New ID:	0.0.0.0	New ID	(Set last four ID)
Content	Rep: 1 HEX Clear	AutoSend Cyc	500 ms 🔲 CutPaper
			³ Print
			Cut Paper
			Open cash drawer
			Traditional
			Driver Print
			+ 4 Advanced
	POS PRINTER TES	ST V3.0C	中文简体
P O S			Copyright(C) JS

"1" Choose Printer Type: "POS-80"

"2" Choose "USB" Port

"3" Click the "Print" to test whether the printer is working.

"4" After doing the above settings, the printer is tested to be working. Then click the "Advanced", and the corresponding window could be popped up.

2. Click the "Advanced". Then the corresponding window is popped up. See the p	icture:
--	---------

Advanced		×
H Parameter Set.	Print H Set Delta 5	
Code page Set	PrintCodePage 0	
NV Logo Test	NV Download	
Barcode Printing test	Print BarCode UPC_A Height	
P76 Buzzer Set	BuzzerSet OFF •	
P76 Density Set	Set NORMAL •	
P80 Black sens:	Set Sensitivity 12 • 12 • SensH	
baud rate set	BaudRate Set (Only P58 and P76E)	
DIP Setting:	P58 Set DIP P80 Set DIP P76 Set DIP	
2D Barcode test	Print 2D Barcode	
Net Setting:	Set Net BluetoothSet	
USB MODE Setting:	USB Printing Virtual COM	
Black Mark Setting:	BlackMarkSet	
File data send:	Open File Send	

3, Click the "Bluetooth Set", and follow the steps to set up the Bluetooth information. See the following pictures:

BT NAME: 1 Printer001	
BT PINKEY:2 1234	
BT USER	
3	

"1" Set up the Port name of the Bluetooth Printer (the Factory Default BT NAME is "Printer001")

"2" Set up the Password of the Bluetooth Printer (the Factory Default BT PINKEY is "123456")

"3" After doing the above settings, click "Setting", and then finished the settings of Bluetooth printer Parameters.

More specific details please refer to "Wireless Thermal Receipt Printer (User Manual)".